



US005845220A

United States Patent [19]
Puthoff

[11] **Patent Number:** **5,845,220**
[45] **Date of Patent:** **Dec. 1, 1998**

[54] **COMMUNICATION METHOD AND APPARATUS WITH SIGNALS COMPRISING SCALAR AND VECTOR POTENTIALS WITHOUT ELECTROMAGNETIC FIELDS**

[75] Inventor: **Harold E. Puthoff**, Austin, Tex.

[73] Assignee: **EarthTech International, Inc.**, San Antonio, Tex.

[21] Appl. No.: **109,983**

[22] Filed: **Aug. 23, 1993**

Related U.S. Application Data

[63] Continuation of Ser. No. 708,331, May 31, 1991, abandoned.

[51] **Int. Cl.⁶** **H04B 1/00**

[52] **U.S. Cl.** **455/899**

[58] **Field of Search** 455/108, 899

[56] **References Cited**

PUBLICATIONS

Y. Aharonov et al., "Significance of Electromagnetic Potentials in the Quantum Theory," *The Physical Review*, 2nd Series, vol. 115, No. 3, Aug. 1, 1959, pp. 485-491.

Y. Aharonov et al., "Further Considerations on Electromagnetic Potentials in the Quantum Theory," *The Physical Review*, vol. 123, No. 4, Aug. 15, 1961, pp. 1511-1524.

Y. Imry et al., "Quantum Interference and the Aharonov-Bohm Effect," *Scientific American*, vol. 260, Apr. 1989, pp. 56-62.

R.P. Feynman et al., *The Feynman Lectures on Physics—Quantum Mechanics*, Addison-Wesley Publishing Company, pp. 21-14-21-18.

B.D. Josephson, "Coupled Superconductors," *Reviews of Modern Physics*, vol. 15, No. 7, 16 Aug. 1965, pp. 295-297.

D.N. Langenberg et al., "Investigation of Microwave Radiation Emitted by Josephson Junctions," *Physical Review Letters*, vol. 15, No. 7, 16 Aug. 1965, pp. 294-297.

R.C. Gelinias, *Curl-Free Vector Potential Effects in a Simply Connected Space*, 1986, Int'l Tesla Society, Inc., pp. 4-43-4-60.


Primary Examiner—Andrew Faile

Attorney, Agent, or Firm—Lowe Hauptman Gopstein Gilman & Berner

[57] **ABSTRACT**

Information that changes as a function of time is communicated from a transmitting site to a receiving site by transmitting a signal comprising scalar and vector potentials without including any electromagnetic field. The potentials vary as a function of time in accordance with the information.

59 Claims, 3 Drawing Sheets






Fig. 1








Fig. 2





72
Fig. 6




Fig. 7

**COMMUNICATION METHOD AND
APPARATUS WITH SIGNALS COMPRISING
SCALAR AND VECTOR POTENTIALS
WITHOUT ELECTROMAGNETIC FIELDS**

This application is a continuation of application Ser. No. 07/708,331 filed May 31, 1991 now abandoned.

FIELD OF THE INVENTION

The present invention relates generally to communication methods and apparatus and, more particularly, to a communication method and apparatus wherein information that changes as a function of time is transmitted by deriving a signal comprising scalar and vector potentials without including an electromagnetic field.

BACKGROUND ART

One of the most common methods of communicating information from one site to another involves transmitting electromagnetic fields containing time varying information commensurate with an information source. Electromagnetic fields are currently employed in the transmission of radio, television and telecommunications signals from a transmitting site to a receiving site. Systems of this type include generators, antennas and receivers designed to generate and detect electromagnetic (E, B) fields. The relationships between the electric (E) and magnetic (B) fields and the generation of these fields by charge sources (ρ) and current sources (J) are governed by Maxwell's equations, namely:

$$\nabla \times E = -\frac{\partial B}{\partial t} \quad (1)$$

$$c^2 \nabla \times B = \frac{J}{\epsilon_0} + \frac{\partial E}{\partial t} \quad (2)$$

$$\nabla \cdot E = \frac{\rho}{\epsilon_0} \quad (3)$$

$$\nabla \cdot B = 0 \quad (4)$$

where

c =the speed of light, and

ϵ_0 =permittivity of free space.

These equations, supplemented by boundary conditions, yield the field distributions for given source configurations.

For particular geometries it is often convenient to introduce, as an intermediary in the solution of Maxwell's equations, the potential functions (A, ϕ) where A is the standard vector potential and ϕ the scalar potential. The potentials (A, ϕ) are related to the fields (E, B) by the defining equations

$$B = \nabla \times A \quad (5)$$

$$E = -\nabla \phi - \frac{\partial A}{\partial t} \quad (6)$$

The electric field E thus consists of an electrostatic component, $\nabla \phi$, and an electrodynamic component, $\partial A / \partial t$. Substitution of Equations (5) and (6) into Maxwell's Equations causes Equations (1)–(4) to reduce to

$$\nabla^2 \phi - \frac{1}{c^2} \frac{\partial^2 \phi}{\partial t^2} = -\frac{\rho}{\epsilon_0} \quad (7)$$

-continued

$$\nabla^2 A - \frac{1}{c^2} \frac{\partial^2 A}{\partial t^2} = -\frac{J}{\epsilon_0 c^2} \quad (8)$$

$$\nabla \cdot A - \frac{1}{c^2} \frac{\partial \phi}{\partial t} \quad (9)$$

Equation (7) determines the scalar potential ϕ in terms of the charge distribution ρ alone, Equation (8) determines the vector potential A in terms of the current distribution J alone, while Equation (9) is a constraining (Lorentz gauge) condition relating the two potentials. From the standpoint of classical electromagnetic theory, use of either the (E, B) or (A, ϕ) formulation is a matter of convenience, and they are considered indistinguishable. Neither is considered more fundamental, and both lead to identical predictions with regard to measurable consequences.

With the advent of quantum theory, however, the above picture changed. In the prior art literature the (A, ϕ) formalism has emerged as more fundamental because it predicts certain quantum interference effects that have been observed and are not apparent from the (E, B) approach. This difference was first set forth in an unequivocal way in a seminal 1959 paper by Aharonov and Bohm, entitled "Significance of Electromagnetic Potentials in the Quantum Theory," *Physical Review* 115, 485 (1959); see also "Further Considerations on Electromagnetic Potentials in the Quantum Theory," *Physical Review* 123, 1511 (1961). In these papers it is shown that in certain two-leg electron-interferometer configurations in which the potentials A and ϕ are established in a region of space, but E and B are absent, it is nonetheless possible for the potentials to induce changes in electron quantum interference patterns. That is, electrons that are in an electromagnetic field-free region and therefore do not encounter an electric or magnetic field are nonetheless acted upon by the presence of the A and/or ϕ potentials. Such an effect is now referred to broadly as the Aharonov-Bohm effect, and devices have been built which demonstrate this effect in the laboratory; for a recent overview, see Y. Imry and R. A. Webb, "Quantum Interference and the Aharonov-Bohm Effect," *Scientific American* 260, 56 (April 1989).

A second quantum interference effect which demonstrates the independent reality of the (A, ϕ) potentials in the absence of the (E, B) fields (and one which is significant for the technology disclosed herein) is a single-leg electron-interferometer effect known as the Josephson effect; see R. P. Feynman et al., *The Feynman Lectures on Physics*, vol. III (Addison-Wesley, Reading, Mass., 1965), pp. 21–14 through 21–18. The Josephson effect is based on the fact that the current density J through a Josephson junction (which consists of two superconductors separated by a thin electric insulator) is determined by the magnitude of the potentials A and ϕ , independent of whether E or B fields are present, in accordance with

$$J = J_0 \sin \left(\delta_0 - \frac{4\pi e}{h} \int A \cdot dr + \frac{4\pi e}{h} \int \phi dt \right) \quad (10)$$

where ϕ is the potential difference across the junction, $\int A \cdot dr$ is evaluated across the junction, δ_0 is an arbitrary phase constant $0 \leq \delta_0 \leq 2\pi$ and e and h are the electronic charge and Planck's constant, respectively, $e=1.602 \times 10^{-19}$ coulombs, $h=6.626 \times 10^{-34}$ joule-sec. By placing a voltage (V) across such a junction (such a voltage is associated with a constant component of ϕ), an oscillating Josephson current is induced which leads to Josephson radiation at a frequency of 483.2 MHz/ μ V; see B. D. Josephson, *Reviews of Modern Physics* 36, 216 (1964). Such radiation is detectable as disclosed by

D. Langenberg, et al., *Physical Review Letters* 15, 294 (1965). If either A or ϕ from an external source is incident on a Josephson junction, the Josephson radiation is modulated and can be detected. Thus, the Josephson effect and the Aharonov-Bohm effect provide proof of the independent significance of the potentials (A, ϕ) upon which the communications technology disclosed herein is based.

In the prior art, the Josephson effect has been proposed as a detector of curl-free vector potential A in the absence of magnetic field B ($B = \nabla \times A = 0$) as has been previously disclosed by Gelinas in U.S. Pat. Nos. 4,429,280, 4,429,288, 4,432,098, 4,447,779, 4,491,795, 4,605,897 and an unpublished paper "Curl-Free Vector Potential Effects in a Simply Connected Space," presented at the 1986 International Tesla/IEEE Symposium, Colorado Springs, Colo. Of the above patents, U.S. Pat. No. 4,429,280 is directed to an apparatus for and method of demodulating a modulated curl-free magnetic vector potential field. A Josephson junction responds to the curl-free magnetic vector potential field to generate a signal including a replica of the modulation imposed on the curl free field. The signal from the junction is coupled to a detector for deriving information that is a replica of information transmitted from a source of the curl free field that may be a current driven toroidal or solenoid source.

THE INVENTION

In accordance with one aspect of the present invention, information that changes as a function of time is communicated from a transmitting site to a receiving site by transmitting a signal having scalar and vector potentials that vary as a function of time in accordance with the information. The transmitted signal does not include an electromagnetic field, i.e., the electromagnetic field is suppressed. In the preferred embodiment, the transmitted signal, as received at the receiving site, is detected with a Josephson junction structure that radiates an electromagnetic wave to a receiver in very close proximity to the Josephson junction. The Josephson junction and receiver for the electromagnetic wave are preferably located in a housing that is shielded for electric and magnetic waves, but which permits the scalar and vector potentials to be transmitted through it.

Hence, the communication method and apparatus of the present invention differs from that disclosed by Gelinas because the present invention employs a suppressed electromagnetic field (i.e. $E=B=0$) and is based on transmission of the vector and scalar potentials only. In the Gelinas device, modulation of the A field for purposes of detection creates a finite non-zero E (i.e., $E \neq 0$) field in accordance with

$$E = - \frac{\partial A}{\partial t}$$

as indicated by Equation (6).

To enable the vector and scalar potentials to be generated while suppressing the electromagnetic field, devices based on Equations (5) and (6) are constructed, subject to the requirement that E and B are set equal to zero. That is, in these devices current (J) and charge (ρ) distributions are formed in radiators, i.e., antennas, to ensure that in the exterior space of interest

$$\nabla \times A = 0 \text{ (i.e., } B = \nabla \times A = 0)$$

-continued

and

$$\nabla \phi = - \frac{\partial A}{\partial t} \text{ (i.e., } E = -\nabla \phi - \frac{\partial A}{\partial t} = 0)$$

In other words, the electromagnetic field is suppressed if the magnetic field is null by virtue of the vector potential being curl-free, and if the electrostatic and electrodynamic fields cancel in time and space.

Cancellation of the electric and magnetic fields in a communication link using vector and scalar potentials between a transmission site and a receiving site in parallel planes extending between the sites is achieved, in accordance with a preferred embodiment of the invention, by generating curl-free vector potential, and electrostatic and electrodynamic fields that are opposed to each other in time and space. To this end, an electrostatic field generator is driven by a voltage source to produce an electrostatic field in the planes. The electrostatic field is in opposition to an electrodynamic field produced by a structure driven by a current source which is configured to generate a curl-free vector potential. These structures for producing the curl-free vector potential, and the cancelling electrostatic and electrodynamic fields are driven by time-derivative-related voltage and current sources exciting them. The amplitudes of the voltage and current applied to the structures which derive the curl-free vector potential, and the electrostatic and electrodynamic fields are adjusted to provide cancellation of the electromagnetic field which otherwise would propagate in the planes.

One advantage of the present invention, alluded to before, is that the vector and scalar potentials penetrate electromagnetic shields. This is because electromagnetic shields work on the principle that incident (E, B) fields induce counter-effects that cancel said incident fields in the shielding materials. Such shielding effects do not occur for signals based solely on vector and scalar potential concepts, frequently referred to hereafter as (A, ϕ) signals. Devices based on the (A, ϕ) concepts are frequently referred to herein as pure-potential devices (PPD's).

A further advantage of the present invention is that prior art electromagnetic receivers do not detect pure-potential signals. The prior art electromagnetic receivers are based on detecting electric and/or magnetic fields, neither of which is present in devices, systems and methods in accordance with the present invention. Hence, the present invention provides an overlapping, parallel use spectrum that exists side by side with the ordinary electromagnetic spectrum. The pure-potential transmission does not interfere with the prior art electromagnetic transmission and vice versa.

It is, accordingly, an object of the present invention to provide a new communication method and apparatus.

Another object of the present invention is to provide an electric communication method and apparatus that does not rely on magnetic, electric, or electromagnetic fields but employs structures resembling those capable of generating magnetic and electric fields.

A further object of the invention is to provide a communication method and apparatus relying on transmission of vector and scalar potentials without the transmission of electromagnetic fields.

Another object of the present invention is to provide a new and improved method of and apparatus for transmitting time-varying information from a site.

An additional object of the present invention is to provide a transmitter of time-varying information, wherein the information is transmitted via vector and scalar potentials, with a suppressed electromagnetic field.

Still another object of the present invention is to provide a receiver that is shielded from electromagnetic, electric and magnetic signals, but which is capable of receiving signals consisting of vector and scalar potentials.

Still a further object of the invention is to provide a new and improved structure for radiating a vector and scalar signal without radiating an electromagnetic signal.

In one of the preferred embodiments of the invention, the pure potential (A, ϕ) signal has variations at a sufficiently low frequency as to enable quasi-static conditions to be established, as occurs for

$$\frac{\partial^2}{\partial t^2} \ll \nabla^2, \text{ i.e., } \frac{\partial^2 A}{\partial t^2} \ll \nabla^2 A, \frac{\partial^2 \phi}{\partial t^2} \ll \nabla^2 \phi.$$

For the quasi-static situation, the (A, ϕ) signal propagates in a near field without an electromagnetic component in certain parallel planes.

The above and still further objects, features and advantages of the present invention will become apparent upon consideration of the following detailed description of several specific embodiments thereof, especially when taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF DRAWING

FIG. 1 is a block diagram of a communications system in accordance with a preferred embodiment of the present invention;

FIG. 2 is a perspective view of one embodiment of a radiator structure including a pair of metal plates and a solenoid that can be employed in the system of FIG. 1 to provide a quasi-stationary near field (A, ϕ) communication link.

FIG. 3 is a top view of the radiator structure illustrated in FIG. 2;

FIG. 4 is a schematic diagram of processing circuitry included in an amplitude modulated transmitter in the system of FIG. 1.

FIG. 5 is a block diagram of processing circuitry included in an angle modulated transmitter in the system of FIG. 1;

FIG. 6 is a schematic diagram of a receiver employed in the system of FIG. 1; and

FIG. 7 is a perspective view of an embodiment of the radiator structure illustrated in FIG. 1 wherein a pair of toroid vector potential generators and metal panels are employed to generate a quasi-stationary near field (A, ϕ) signal.

DESCRIPTION OF THE PREFERRED EMBODIMENT

Reference is now made to FIG. 1 of the drawing wherein there is illustrated a time-varying signal source **11**, such as an analog voice source. Signal source **11** drives processing circuit **13** to cause the circuit to derive a pair of time-derivative-related signals (one being effectively the time derivative of the other) on leads **15** and **17**. The time-derivative-related signals on leads **15** and **17** are applied to radiator structure **19** which causes a vector and scalar potential signal (A, ϕ) containing the information of signal source **11** to be transmitted.

The signal transmitted from radiator structure **19** has a suppressed, i.e., zero, electromagnetic field in certain parallel planes extending between radiator structure **19** and receiver structure **21**. The (A, ϕ) signal radiates in the parallel planes in which the electromagnetic field is sup-

pressed between radiator structure **19** and receiver **21**. Vector and scalar potentials of the (A, ϕ) signal vary as a function of the variations of signal source **11**. To suppress the electromagnetic field, radiator structure **19** produces a curl-free vector potential, as well as electrostatic and electrodynamic fields that are in opposition to each other in time and space. In addition, the relative amplitudes of the signals on leads **15** and **17** are properly adjusted by processing circuit **13** to suppress the electromagnetic field (E, B) in these parallel planes. The vector potential and electrostatic field generating structures in radiator structure **19** are driven by time-derivative-related current and voltage sources that are responsive to the signal of source **11**.

If the vector and scalar potentials vary slowly in time such that they are considered quasi-static, i.e.,

$$\partial^2/\partial t^2 \ll \nabla^2, \quad (11)$$

Equations (5)–(9) reduce to

$$\nabla \cdot \mathbf{x}A = 0, \nabla \phi = -\frac{\partial A}{\partial t}, \nabla^2 \phi = 0. \quad (12)$$

To achieve these results radiator structure **19** is excited by the signals on leads **15** and **17** to enable (a) a curl-free vector potential ($\nabla \times \mathbf{A} = 0$) to be derived and (b) electric field effects associated with the scalar and vector potentials to cancel, i.e.,

$$\nabla \phi = -\frac{\partial A}{\partial t};$$

this loosely implies that the electrostatic and electrodynamic field effects derived from the radiator structure cancel. A pair of radiator structures which generate potential distributions satisfying these requirements are described infra. These radiator structures transmit quasi-static suppressed electromagnetic signals having vector and scalar potentials (A, ϕ).

Receiver **21** is a quantum interference receiver of the Josephson junction type. The receiver is preferably located in shield **23** for electromagnetic, magnetic and electrostatic fields; shield **23** includes, for example, a mu metal screen superposed with a copper or aluminum screen. The shield is pervious to the vector and scalar potential (A, ϕ) signal.

Receiver **21** includes, in the preferred embodiment, a thin dielectric sheet sandwiched between a pair of superconductors in an appropriate cryogenic environment. The superconductors are biased by a DC source so that the Josephson junction of quantum interference receiver **21** normally radiates electromagnetic energy at a predetermined radio frequency. In response to the (A, ϕ) wave from radiator structure **19** penetrating the magnetic and electrostatic shield **23** surrounding quantum interference receiver **21** and being incident on the Josephson junction, the radio frequency radiation emitted by the Josephson junction is modulated. The modulation is a replica of the variations of the (A, ϕ) wave incident on the Josephson junction. The modulated radiation from the Josephson junction is coupled, basically as an electromagnetic wave, to conventional electromagnetic wave radio receiver **22**, also located within shield **23** so that the electromagnetic wave is not radiated outside of the shield. Receiver **22** is connected by a cable (not shown) to processing circuitry that is either inside or external to shield **23**.

Reference is now made to FIGS. 2 and 3 of the drawing wherein there is illustrated one preferred embodiment of radiator structure **19** for deriving a near field, quasi-static ($A,$

ϕ) suppressed electromagnetic signal that radiates from the transmitter to receiver **21** in horizontal planes. The structure of FIGS. **2** and **3** includes solenoid coil **31** (positioned so axis **33** thereof extends vertically) in combination with planar non-magnetic metal panels **35** and **37** that extend in the vertical plane. Panels **35** and **37** can be configured as plates or screens; hereafter they are generally referred to as plates. Plates **37** and **39** are arranged so that projections of the planes thereof intersect axis **33**. The angular separation between plates **37** and **39** determines the gain and directivity of the (A, ϕ) signal derived from structure **19**.

Solenoid **31** is driven by current source **55** to produce a vertically directed magnetic field (B) within the solenoid and a curl-free vector potential exterior to the solenoid. Plates **35** and **37** are driven by voltage source **53** to produce an electrostatic field in the horizontal plane. The voltage applied to plates **35** and **37** varies as the time derivative of the current applied to solenoid **31**. The amplitudes of the current driving solenoid **31** and the voltage driving plates **35** and **37** are adjusted so that a curl-free vector potential is generated, and the electrostatic and electrodynamic fields from the solenoid and plates cancel in the horizontal planes in the near field which causes the electromagnetic field to be suppressed in the horizontal planes. The fields from solenoid **31** and plates **35** and **37**, however, combine in the horizontal planes to produce modulated vector and scalar potentials (A, ϕ) that cause a signal to be transmitted in the horizontal plane from the solenoid and plates to receiver **21**. The magnetic field (B) in solenoid **31** is given by

$$B = 1_z \mu_0 \left(\frac{N}{d} \right) I(t)$$

where:

1_z =the unit vector in the vertical (z) direction

μ_0 =magnetic permeability of free space ($4\pi \times 10^{-7}$ HM⁻¹)

$I(t)$ =current flowing in the solenoid

N/d =number of turns per unit length.

Associated with the magnetic field B trapped in solenoid **31** is the potential vector (A), which is given by

$$A = 1_\theta \mu_0 \left(\frac{N}{d} \right) \frac{a^2}{2r} I(t)$$

where:

1_θ =the unit angular vector in a plane at right angles to axis **33** of solenoid **31**

a =the radius of solenoid **31** from axis **33**

r =the distance of vector potential field line (A) from axis **33**.

The scalar potential ϕ in the horizontal plane at an angle θ from one of plates **35** or **37** is given by

$$\phi = - \frac{V(t)}{\Omega} \theta$$

where:

$V(t)$ =voltage between plates **35** and **37**

Ω =total angular separation between plates **35** and **37**.

Because the magnetic field B produced by solenoid **31** is confined to the interior of the solenoid, the curl-free vector potential A is incident on receiver **21**. If cosine and sine waves $V_m \cos \omega t$ and $I_m \sin \omega t$ are supplied to leads **15** and **17**, the electrostatic field from plates **35** and **37** and the electrodynamic field from coil **31** can be adjusted to cancel

and thereby suppress the E-field between the plates if:

$$E = - \nabla \phi - \frac{\partial A}{\partial t} = 1_\theta \left[\frac{V_m \cos \omega t}{\Omega r} - \mu_0 \left(\frac{N}{d} \right) \frac{a^2}{2r} \frac{\partial (I_m \sin \omega t)}{\partial t} \right] = 0$$

where:

$\omega = 2\pi f$

f =frequency of the voltage applied to plates **35** and **37** and of the current applied to coil **31**.

While the radiator structure of FIGS. **2** and **3** has been illustrated and described as transmitting the (A, ϕ) signal with a suppressed electromagnetic field in horizontally extending planes, it is to be understood that the radiator structure could be designed to transmit the (A, ϕ) signal in mutually parallel planes at any inclination; the propagation planes are at right angles to axis **33** of solenoid **31**. The radiator structure is arranged so plates **35** and **37** and axis **33** all lie in planes that are at right angles to a common plane in which the (A, ϕ) signal is transmitted.

One embodiment of processing circuit **13** for enabling amplitude modulated time varying vector and scalar potentials (A, ϕ) to be transmitted from radiator structure **19** to receiver **21** is illustrated in FIG. **4**. In FIG. **4**, signal source **11** is an audio frequency source, such as a voice source having multiple frequencies. The signal from source **11** is supplied to amplitude modulator **41**, driven by a carrier having a frequency sufficiently low to enable the quasi-static conditions to be met. (In an actual experiment, it was found that the quasi-static conditions can be met easily for frequencies equal at least to 1.5 MHz.) The amplitude modulated output signal of modulator **41** is applied in parallel to differentiator **43** and amplifier **51**, having a gain A_2 . Differentiator **43** has an output that is supplied to amplifier **49**, having a gain A_1 . The output signals of amplifiers **49** and **51** are thereby time-derivative-related. The values of A_1 and A_2 are adjusted to enable the near electromagnetic field from radiator structure **19** to be suppressed in the horizontal planes. The signals derived from amplifiers **49** and **51** are respectively applied to voltage source **53** and current source **55**. Sources **53** and **55** are two terminal output devices, with the voltage developed by source **53** being applied to plates **35** and **37** and the current derived from source **55** being applied to solenoid **31**.

Reference is now made to FIG. **5**, a block diagram of processing circuitry **13** for enabling an electromagnetic suppressed, pure potential (A, ϕ) signal to be transmitted as an angle modulated wave from radiator structure **19** to receiver **21**. Signal source **11** may be a relatively low variable frequency source, such as a speech source. The output of source **11** is applied to angle modulator **61**, which can be either a frequency or phase modulator, also responsive to a carrier wave having a frequency sufficiently low to enable the quasi-static conditions associated with the radiator of FIGS. **2** and **3** to be achieved. Modulator **61** derives an FM or PM output that is applied in parallel to differentiator **63** and amplifier **65**, having a gain A_2 . Differentiator **63** has an output that is supplied to amplifier **67**, having a gain A_1 . The output signals of amplifiers **65** and **67** are thereby time-derivative-related; the values of A_1 and A_2 cause the amplitude of the electromagnetic signal derived from radiator structure **19** to be suppressed. The output signals of amplifiers **65** and **67** are respectively supplied to current source **69** and voltage source **71** which drive solenoid **31** and plates **35, 37** of radiator structure **19** in the same

manner described supra with regard to voltage and current sources **53** and **55**.

Reference is now made to FIG. 6 of the drawing, a schematic diagram of the apparatus preferably included in receiver **21**. As indicated supra, receiver **21** is a quantum interference receiver including Josephson junction **72**, formed of horizontally disposed thin electric insulator **73**, sandwiched between opposed planar end faces of Type I superconductor rods **75** and **77**. Josephson junction structure **72** is located in an appropriate cryogenic environment, as well known to those skilled in the art. DC voltage source **79** has opposite electrodes connected to superconductors **75** and **77**. In response to no signal energy being incident on Josephson junction **72**, electromagnetic radiation having a predetermined frequency, governed by the amplitude of the voltage applied by source **79** to the junction, is radiated from the junction. The amplitude and frequency of the electromagnetic radiation radiated by Josephson junction **72** are modulated by the (A, ϕ) signal incident on the junction, as radiated from radiator structure **19** and received by receiver **21**, after propagating through magnetic and electric shield **23**. The amplitude and frequency of the modulated radiation emitted by the Josephson junction are coupled to and received by electromagnetic receiver **22**, located in shield **23**.

A further embodiment of a near field radiator structure for a quasi-static vector and scalar potential (A, ϕ) signal with suppressed electromagnetic energy in horizontal planes is illustrated in FIG. 7 as including metal screens **81** and **83** and toroidal coils **85** and **87**, all of which are arranged so they extend parallel to each other in mutual parallel vertical planes. Screens **81** and **83** are respectively in close proximity to coils **85** and **87**. Coils **85** and **87** have a common axis **89**, extending in the horizontal plane. Hence, the magnetic fields that circulate within toroidal coils **85** and **87** are at right angles to the electric field established between screens **81** and **83** so that the vector potential and electrodynamic fields derived from the toroidal coils and the electric fields derived from the screens can, if properly phased and adjusted to the correct amplitude, interact to produce time varying vector and scalar potential (A, ϕ) signals without producing an electromagnetic field.

Screens **81** and **83** are driven by voltage source **91**, while toroidal coils **85** and **87** are driven in parallel by current source **93**. The voltage and current applied by sources **91** and **93** to screens **81** and **83** and to toroidal coils **85** and **87** are time-derivative phased and adjusted in amplitude, as described supra, to provide a time varying (A, ϕ) signal having no electromagnetic component in the same planes as the (A, ϕ) signal radiates.

While there have been described and illustrated specific embodiments of the invention, it will be clear that variations in the details of the embodiments specifically illustrated and described may be made without departing from the true spirit and scope of the invention as defined in the appended claims. For example, the invention is not limited to near field devices, but is also applicable to far field, radiation transmission devices wherein the quasi-static conditions need not subsist. To this end, the antennas are structured and driven to generate field distributions that satisfy the pure-potential requirement established in Equations (11) and (12). Also, it is not necessary for the radiators to be driven by sine waves that, in order to meet the time-derivative-relation requirement, are quadrature phased. If the signal source is, for example, a triangular wave, the time-derivative relationship is derived by differentiating the triangular wave into a square wave such that the square and triangular waves are

respectively supplied by the voltage and current sources to the panel and coil arrangements.

I claim:

1. A method of communicating information that changes as a function of time from a first site to a second site comprising transmitting a signal that varies as a function of time in accordance with the information from the first site to the second site, the signal having scalar and vector potentials without including an electromagnetic field, receiving the transmitted signal at the second site, and detecting the information from the signal as received at the second site.

2. The method of claim 1 wherein the signal is generated by deriving a curl-free vector potential, and electrostatic and electrodynamic fields that are mutually opposed in time and space and which vary as a function of time in accordance with the information and have amplitudes to cause the derived electrostatic and electrodynamic fields to cancel.

3. The method of claim 2 wherein the curl-free vector potential, and the cancelling electrostatic and electrodynamic fields are derived from electrostatic and vector potential generating structures respectively driven by voltage and current sources deriving controlled phased outputs which suppress electromagnetic fields but retain scalar and vector potentials which vary as a function of time in accordance with the information.

4. The method of claim 2 wherein the curl-free vector potential, and the cancelling electrostatic and electrodynamic fields are derived from electrostatic and vector potential generating structures respectively driven by voltage and current sources deriving first and second outputs such that one of the outputs is the time derivative of the other output.

5. The method of claim 1 wherein the signal is received at the second site by a quantum interference receiver.

6. The method of claim 5 wherein the quantum interference receiver is in a shield for magnetic and electric energy but which is pervious to scalar and vector potentials.

7. The method of claim 1 wherein the signal is a near field signal and the second site is in the near field of radiation from the first site.

8. The method of claim 7 wherein the information is at a frequency causing the transmitted signal to be quasi-static.

9. The method of claim 1 wherein the information is at a frequency causing the transmitted signal to be quasi static.

10. The method of claim 9 wherein the signal is amplitude modulated as a function of time in response to the information.

11. The method of claim 9 wherein the signal is angle modulated as a function of time in response to the information.

12. The method of claim 1 wherein the signal is amplitude modulated as a function of time in response to the information.

13. The method of claim 1 wherein the signal is angle modulated as a function of time in response to the information.

14. A method of transmitting information that changes as a function of time comprising transmitting a signal having scalar and vector potentials without including an electromagnetic field, the signal varying as a function of time in accordance with the information.

15. The method of claim 14 wherein the signal is generated by deriving curl-free vector potentials and electrostatic and electrodynamic fields that are mutually opposed in time and space and which vary as a function of time in accordance with the information and have amplitudes to cause the derived electrostatic and electrodynamic fields to cancel.

16. The method of claim 15 wherein the curl-free vector potential, and the electrostatic and electrodynamic fields are

derived from scalar and vector potential generating structures respectively driven by voltage and current sources deriving selectively phased outputs which suppress electromagnetic fields but retain scalar and vector potentials which vary as a function of time in response to the information. 5

17. The method of claim 15 wherein the curl-free vector potential, and the cancelling electrostatic and electrodynamic fields are derived from electrostatic and vector potential generating structures respectively driven by voltage and current sources deriving controlled phased outputs which suppress electromagnetic fields but retain scalar and vector potentials which vary as a function of time in accordance with the information. 10

18. The method of claim 14 wherein the signal is a near field wave. 15

19. The method of claim 18 wherein the information is at a frequency causing the transmitted signal to be quasi-static.

20. The method of claim 14 wherein the information is at a frequency causing the transmitted signal to be quasi-static.

21. The method of claim 20 wherein the signal is amplitude modulated as a function of time in response to the information. 20

22. The method of claim 20 wherein the signal is angle modulated as a function of time in response to the information. 25

23. The method of claim 14 wherein the signal is amplitude modulated as a function of time in response to the information. 30

24. The method of claim 14 wherein the signal is angle modulated as a function of time in response to the information. 35

25. A communication transmitter comprising a source of a time varying input signal, and means responsive to the signal for deriving a transmitted signal having scalar and vector potentials without including an electromagnetic field, the transmitted signal varying as a function of time in accordance with the input signal. 40

26. The communication transmitter of claim 25 wherein the means for deriving the transmitted signal includes means for deriving a curl-free vector potential, and electrostatic and electrodynamic fields that are mutually opposed in time and space and which vary as a function of time in accordance with the input signal and have amplitudes to cause the derived electrostatic and electrodynamic fields to cancel. 45

27. The communication transmitter of claim 26 wherein the means for deriving the transmitted signal further includes electrostatic and vector potential generating structures, a voltage source connected to drive the electrostatic field generating structure, a current source connected to the vector potential generating structure, the current and voltage sources being connected to be responsive to the input signal and arranged to supply time-derivative-related currents and voltages to the vector potential and electrostatic field generating structures. 50

28. The communication transmitter of claim 27 wherein the electrostatic field generating structure includes a pair of spaced metal planar panels extending in the same directions, the vector potential generating structure including at least one coil. 55

29. The communication transmitter of claim 28 wherein projections of the panels intersect on a line, the coil being a solenoid having an axis coincident with the line. 60

30. The communication transmitter of claim 28 wherein the coil is a toroid having an axis at right angles to the planes of the panels. 65

31. The communication transmitter of claim 30 wherein the panels are in mutually parallel planes.

32. The communication transmitter of claim 28 wherein a pair of the coils is provided, each of the coils being a toroid, both toroids having a common axis at right angles to the planes of the panels.

33. The communication transmitter of claim 32 wherein the panels are in mutually parallel planes.

34. A communication transmitter comprising a source of a time varying input signal, and means responsive to the signal for deriving a transmitted signal, the transmitted signal deriving means including means for deriving a curl-free vector potential, and electrostatic and electrodynamic fields that are mutually opposed in time and space and which vary as a function of time in accordance with the input signal. 15

35. The communication transmitter of claim 34 wherein the amplitudes of the electrostatic and electrodynamic fields are such as to cause the derived electrostatic and electrodynamic fields to cancel. 20

36. The communication transmitter of claim 34 wherein the means for deriving the transmitted signal further includes electrostatic and vector potential generating structures, a voltage source connected to drive the electrostatic field generating structure, a current source connected to drive the vector potential generating structure, the current and voltage sources being connected to be responsive to the input signal and arranged to supply time-derivative-related currents and voltages to the vector potential and electrostatic field generating structures. 25

37. The communication transmitter of claim 36 wherein the electrostatic field generating structure includes a pair of spaced metal planar panels extending in the same directions, the vector potential generating structure including at least one coil. 30

38. The communication transmitter of claim 37 wherein projections of the panels intersect on a line, the coil being a solenoid having an axis coincident with the line. 35

39. The communication transmitter of claim 37 wherein the coil is a toroid having an axis at right angles to the planes of the panels. 40

40. The communication transmitter of claim 39 wherein the panels are in mutually parallel planes. 45

41. The communication transmitter of claim 37 wherein a pair of the coils is provided, each of the coils being a toroid, both toroids having a common axis at right angles to the planes of the panels. 50

42. The communication transmitter of claim 41 wherein the panels are in mutually parallel planes. 55

43. A signal deriving structure comprising an electrostatic field generating structure, a vector potential generating structure, the field generating structures being arranged to derive a curl-free vector potential, and electrostatic and electrodynamic fields that are mutually opposed in time and space and which vary as a function of time in accordance with information from an input signal source, the amplitudes of the electrostatic and electrodynamic fields being such as to cause the derived electrostatic and electrodynamic fields to cancel. 60

44. The structure of claim 43 further including a voltage source connected to drive the electrostatic field generating structure, a current source connected to drive the vector potential generating structure, the current and voltage sources being connected to be responsive to the input signal source and arranged to supply mutually time-derivative-related currents and voltages to the vector potential and electrostatic field generating structures. 65

45. The structure of claim 44 wherein the electrostatic field generating structure includes a pair of spaced metal

13

planar panels extending in the same directions, the vector potential generating structure including at least one coil.

46. The structure of claim 45 wherein projections of the panels intersect on a line, the coil being a solenoid having an axis coincident with the line.

47. The structure of claim 45 wherein the coil is a toroid having an axis at right angles to the planes of the panels.

48. The structure of claim 47 wherein the panels are in mutually parallel planes.

49. The structure of claim 45 wherein a pair of the coils is provided, each of the coils being a toroid, both toroids having a common axis at right angles to the planes of the panels.

50. The structure of claim 49 wherein the panels are in mutually parallel planes.

51. The structure of claim 43 wherein the electrostatic field generating structure includes a pair of spaced metal planar panels extending in the same directions, the vector potential generating structure including at least one coil.

52. The structure of claim 51 wherein projections of the panels intersect on a line, the coil being a solenoid having an axis coincident with the line.

53. The structure of claim 51 wherein the coil is a toroid having an axis at right angles to the planes of the panels.

54. The structure of claim 53 wherein the panels are in mutually parallel planes.

14

55. The structure of claim 52 wherein a pair of the coils is provided, each of the coils being a toroid, both toroids having a common axis at right angles to the planes of the panels.

56. The structure of claim 55 wherein the panels are in mutually parallel planes.

57. In combination, a quantum interference receiving structure for a scalar and vector potential signal, and a shield for electromagnetic waves enclosing said receiving structure, the shield being permeable to said scalar and vector potential signal.

58. The combination of claim 57 wherein the receiving structure includes a biased Josephson junction on which the scalar and vector potential signal is incident.

59. The combination of claim 57 wherein the receiving structure includes a Josephson junction on which the scalar and vector potential signal is incident, means for biasing the junction to cause the junction to emit electromagnetic radiation, variations of the scalar and vector potential signal incident on the junction causing modulation of the emitted electromagnetic radiation, and a receiver responsive to the emitted electromagnetic radiation, the receiver being enclosed by the shield.

* * * * *